



SPC Schlüsselschalter-Erweiterungsmodul

Das SPCE110 kombiniert mit einer SPC bietet dem Kunden die Möglichkeit über eine einfache und sichere Bedieneinheit die SPC Zentrale zu bedienen.

Key Features

- Bedienung der Einbruchmeldeanlage
- Einfache Konfiguration
- Integration in die Trigger-Programmierung
- Frei programmierbarer Relaisausgang
- Universal konfigurierbare LEDs
- Ansteuerung der Ausgänge über Kalender einschränkbar

Die wichtigsten Zahlen

- 3 Schlüsselpositionen
- 2 Status LEDs
- 1 Relaisausgang

Key Positions

- Unscharf
- Scharf
- Intern Scharf
- Unscharf – extern Scharf
- Unscharf – Intern Scharf
- Alles in Ordnung
- Freigabe für Bedienteil
- Oder Anzeigemodul



Technische Daten

Funktionale

LED-Anzeigen	2 dreifarbige LEDs
Anzahl Relaisausgänge auf Platine	1 (Einpölicher Umschalter, 30 VDC / max. 1 A Ohmsche Belastung)
Programmierbare Schlüsselpositionen	3 Schlüsselpositionen (2-0-1 in 90° Schritten, Zylindertyp KABA1008C)

Einbruchmeldetechnik

Schnittstellen	X-BUS (Ein- /Ausgang)
----------------	-----------------------

Strom und Mechanik

Abmessungen (B x H x T)	112 x 92 x 38 mm
Gehäuse	Kunststoffgehäuse (ABS)
Arbeitsstrom	Max. 50 mA bei 12 VDC (Relais und LEDs aktiv)
Betriebstemperatur	-10 ~ +50 °C
Betriebsspannung	9.5 - 14 VDC
Ruhestrom	Max. 30 mA bei 12 VDC
Sabotagekontakt	Deckelkontakt / Abreisskontakt

Allgemein

Zulassung	DE: VdS G112129, Klasse C (darf aber NICHT als VdS Schliesseinrichtung benutzt werden) AT: W 130923/10 E, Klasse WS CH: SES EN CH Grade 3
Farbe	RAL 9003 (Signalweiss)
Befestigung	Wandmontage Aufputz
Gewicht	0.270 kg

Bestelldaten

Type	Art. No.	Description	Weight*
Expander	V54542-F104-A100	SPCE110	0.270 kg

* Total weight of the product inclusive of the weight of its accessories and packaging.

Zusätzliche Bestelldaten

Acre intrusion Panels

Type	Art. No.	Description
SPC6350.320-L1	V54541-C118-A100	acre intrusion control panel, 16-512 zones, Ethernet, G5 metal housing
SPC6330.320-L1	V54541-C105-C100	acre intrusion control panel, 8-512 zones, Ethernet, G3 metal housing
SPC5350.320-L1	V54541-C117-A100	acre intrusion control panel, 16-128 zones, Ethernet, G5 metal housing
SPC5330.320-L1	V54541-C107-B100	acre intrusion control panel, 8-128 zones, Ethernet, G3 metal housing
SPC5320.320-L1	V54541-C106-B100	acre intrusion control panel, 8-128 zones, Ethernet, G2 metal housing
SPC4320.320-L1	V54541-C109-B100	acre intrusion control panel, 8-32 zones, Ethernet, G2 metal housing
SPC4320.220-L1	V54541-C114-A100	acre intrusion control panel, 8-32 zones, Ethernet, G2 housing with metal base and plastic cover

Keypads

Type	Art. No.	Description
SPCK520.100-N	V54543-F115-A100	Compact Keypad with graphical display and audio
SPCK521.100-N	V54543-F116-A100	Compact Keypad with graphical display, card reader and audio
SPCK620.100	V54543-F110-A100	LCD keypad with graphical display
SPCK623.100	V54543-F111-A100	LCD keypad with graphical display, card reader and audio
SPCK420.100	V54543-F101-A100	LCD keypad with 2 x 16 characters
SPCK421.100	V54543-F102-A100	LCD keypad with 2 x 16 characters and integrated card reader

Detectors

Type	Art. No.	Description
PDM-I12	V54530-F114-A100	MAGIC PIR detector, 12m wide angle
PDM-I18	V54530-F106-A100	MAGIC PIR detector, 18 m wide angle
MK-1400	V54536-F101-A100	Magnetic contact

Accessories

Type	Art. No.	Description
IPAW8-10	V54538-F107-A100	Wireless personal alarm
IRCW6-11	V54543-F109-A100	SiWay remote control, white replaceable battery
IPAW6-10	V54538-F108-A100	Wireless Personal Alarm Button

Expanders

Type	Art. No.	Description
SPCE452.100	V54542-F107-A100	Expander with 8 outputs, back tamper
SPCE652.100	V54542-F106-A100	Expander with 8 inputs and 2 outputs, back tamper
SPCA210.100	V54547-A101-A100	2-door expander
SPCP432.300	V54545-C103-A100	Smart PSU with 2-door expander, G2-housing
SPCP433.300	V54545-C104-A100	Smart PSU with 2-door expander, G3-housing
SPCE110.100	V54542-F104-A100	Keyswitch expander with 2 LEDs and 3-position key switch
SPCE120.100	V54542-F105-A100	Indication expander with 16 LEDs, 4 function keys and integrated card reader
SPCW130.100	V54554-F101-B100	SiWay RF-expander
SPCP332.300	V54545-C102-A100	Smart PSU with 8 inputs and 2 outputs, G2-housing
SPCP333.300	S54545-C101-A100	Smart PSU with 8 inputs and 2 outputs, G3-housing
SPCP355.300	S54545-C105-A100	Smart PSU with 8 inputs and 6 outputs, G5 metal housing

Verification

Type	Art. No.	Description
SPCV340.000	V54542-F108-B100	Audio expander with 4 inputs and 1 output
SPCV341.000	V54542-F109-B100	Audio expander with 4 inputs and 1 line output
SPCV310.000	V54542-F120-A100	Audio satellite
SPCV440.000	V54542-F118-A100	Combi audio expander for MAGIC motion detectors with 4 inputs and 1 output
SPCV410.000	V54542-F119-A100	Combi audio satellite for MAGIC motion detectors
CCMS2010-IR	S54561-C112-A100	1/2.7" 2MP Compact IP Camera PoE(LAN)

Access

Type	Art. No.	Description
HFS LWA AES / CDA2	V54547-Z101-A100	HF reader
HFS TKWA AES / CDA2	V54547-Z102-A100	HF reader with keypad
HFS LWA APW / CDA2	V54547-Z101-A200	HF reader
HFS TKWA-APW / CDA2	V54547-Z102-A200	HF reader with keypad
AR6181-MX	6FL7170-8BK	Multi-technology card reader
PP500-EM	V54501-F1-A1	Heavy-duty card and PIN reader
AR6182-RX	6FL7170-8AE	Multi-technology card and PIN reader