



## Módulo SPC de control mediante llave de 3 posiciones

Conectado al X Bus de SPC, el módulo SPCE110 de Vanderbilt permite ejecutar ciertas funciones, previamente configuradas, mediante la simple maniobra de una llave.

### Key Features

- Control de ciertas funciones del sistema de intrusión
- Fácil configuración
- Integración en la funcionalidad causa/efecto (macros)
- Cilindro de cerradura intercambiable
- Salida de relé, programable
- Indicadores LED de funcionamiento programable

### Key Numbers

- Llave de 3 posiciones
- 2 LEDs de estado
- 1 salida de relé

### Key Positions

- Armado y desarmado con enclavamiento o con retorno.
- Todo OK
- Autorización de armado



## Technical Data

### Funcionalidad

|                          |  |
|--------------------------|--|
| Indicadores LED          | 2 LEDs tri-color   |
| Número de relés en placa | 1 (contacto conmutado, 30 VDC / max. 1 A de corriente conmutación resistiva) |
| Llave programable        | 3 key positions (2-0-1 in 90° steps, cylinder type KABA1008C)                |

### Intrusion

|            |                         |
|------------|-------------------------|
| Interfaces | X-BUS (entrada, salida) |
|------------|-------------------------|

### Alimentación y medidas

|                             |   |
|-----------------------------|---|
| Dimensiones (A x H x F)     | 112 x 92 x 38 mm  |
| Carcasa                     | Plástico (Policarbonato)                                    |
| Corriente de funcionamiento | Max. 50 mA at 12 VDC (con todos los relés y LEDs activados) |
| Temperatura de operación    | -10 ~ +50 °C  |
| Tensión de operación        | 9.5 - 14 VDC  |
| Corriente en reposo         | Max. 30 mA a 12 VDC   |
| Tamper                      | Tamper frontal y trasero (antidespegue) mediante muelles    |

### General

|              |   |
|--------------|---|
| Homologación | EN50131-1 / EN50131-3, Grado 3, Class II<br>UK: PD6662:2010<br>BE: INCERT |
| Color        | RAL 9003 (blanco señal)   |
| Montaje      | Superficie plana, montado en la pared                                     |
| Peso         | 0.270 kg  |

## Ordering Data

| Type     | Art. No.         | Description | Weight*  |
|----------|------------------|-------------|----------|
| Expander | V54542-F104-A100 | SPCE110     | 0.270 kg |

\* Total weight of the product inclusive of the weight of its accessories and packaging.

## Additional Ordering Data

### Acre intrusion Panels

| Type           | Art. No.         | Description  |
|----------------|------------------|--|
| SPC6350.320-L1 | V54541-C118-A100 | acre intrusion control panel, 16-512 zones, Ethernet, G5 metal housing                           |
| SPC6330.320-L1 | V54541-C105-C100 | acre intrusion control panel, 8-512 zones, Ethernet, G3 metal housing                            |
| SPC5350.320-L1 | V54541-C117-A100 | acre intrusion control panel, 16-128 zones, Ethernet, G5 metal housing                           |
| SPC5330.320-L1 | V54541-C107-B100 | acre intrusion control panel, 8-128 zones, Ethernet, G3 metal housing                            |
| SPC5320.320-L1 | V54541-C106-B100 | acre intrusion control panel, 8-128 zones, Ethernet, G2 metal housing                            |
| SPC4320.320-L1 | V54541-C109-B100 | acre intrusion control panel, 8-32 zones, Ethernet, G2 metal housing                             |
| SPC4320.220-L1 | V54541-C114-A100 | acre intrusion control panel, 8-32 zones, Ethernet, G2 housing with metal base and plastic cover |

### Keypads

| Type          | Art. No.         | Description  |
|---------------|------------------|--|
| SPCK520.100-N | V54543-F115-A100 | Compact Keypad with graphical display and audio              |
| SPCK521.100-N | V54543-F116-A100 | Compact Keypad with graphical display, card reader and audio |
| SPCK620.100   | V54543-F110-A100 | LCD keypad with graphical display                            |
| SPCK623.100   | V54543-F111-A100 | LCD keypad with graphical display, card reader and audio     |
| SPCK420.100   | V54543-F101-A100 | LCD keypad with 2 x 16 characters                            |
| SPCK421.100   | V54543-F102-A100 | LCD keypad with 2 x 16 characters and integrated card reader |

### Detectors

| Type    | Art. No.         | Description                         |
|---------|------------------|-------------------------------------|
| PDM-I12 | V54530-F114-A100 | MAGIC PIR detector, 12m wide angle  |
| PDM-I18 | V54530-F106-A100 | MAGIC PIR detector, 18 m wide angle |
| MK-1400 | V54536-F101-A100 | Magnetic contact                    |

### Accessories

| Type     | Art. No.         | Description                                     |
|----------|------------------|---|
| IPAW8-10 | V54538-F107-A100 | Wireless personal alarm                         |
| IRCW6-11 | V54543-F109-A100 | SiWay remote control, white replaceable battery |
| IPAW6-10 | V54538-F108-A100 | Wireless Personal Alarm Button                  |

## Expanders

| Type        | Art. No.         | Description  |
|-------------|------------------|--|
| SPCE452.100 | V54542-F107-A100 | Expander with 8 outputs, back tamper   |
| SPCE652.100 | V54542-F106-A100 | Expander with 8 inputs and 2 outputs, back tamper                            |
| SPCA210.100 | V54547-A101-A100 | 2-door expander  |
| SPCP432.300 | V54545-C103-A100 | Smart PSU with 2-door expander, G2-housing                                   |
| SPCP433.300 | V54545-C104-A100 | Smart PSU with 2-door expander, G3-housing                                   |
| SPCE110.100 | V54542-F104-A100 | Keyswitch expander with 2 LEDs and 3-position key switch                     |
| SPCE120.100 | V54542-F105-A100 | Indication expander with 16 LEDs, 4 function keys and integrated card reader |
| SPCW130.100 | V54554-F101-B100 | SiWay RF-expander  |
| SPCP332.300 | V54545-C102-A100 | Smart PSU with 8 inputs and 2 outputs, G2-housing                            |
| SPCP333.300 | S54545-C101-A100 | Smart PSU with 8 inputs and 2 outputs, G3-housing                            |
| SPCP355.300 | S54545-C105-A100 | Smart PSU with 8 inputs and 6 outputs, G5 metal housing                      |

## Verification

| Type        | Art. No.         | Description  |
|-------------|------------------|--|
| SPCV340.000 | V54542-F108-B100 | Audio expander with 4 inputs and 1 output                                  |
| SPCV341.000 | V54542-F109-B100 | Audio expander with 4 inputs and 1 line output                             |
| SPCV310.000 | V54542-F120-A100 | Audio satellite  |
| SPCV440.000 | V54542-F118-A100 | Combi audio expander for MAGIC motion detectors with 4 inputs and 1 output |
| SPCV410.000 | V54542-F119-A100 | Combi audio satellite for MAGIC motion detectors                           |
| CCMS2010-IR | S54561-C112-A100 | 1/2.7" 2MP Compact IP Camera PoE(LAN)                                      |

## Access

| Type                | Art. No.         | Description                          |
|---------------------|------------------|--------------------------------------|
| HFS LWA AES / CDA2  | V54547-Z101-A100 | HF reader                            |
| HFS TKWA AES / CDA2 | V54547-Z102-A100 | HF reader with keypad                |
| HFS LWA APW / CDA2  | V54547-Z101-A200 | HF reader                            |
| HFS TKWA-APW / CDA2 | V54547-Z102-A200 | HF reader with keypad                |
| AR6181-MX           | 6FL7170-8BK      | Multi-technology card reader         |
| PP500-EM            | V54501-F1-A1     | Heavy-duty card and PIN reader       |
| AR6182-RX           | 6FL7170-8AE      | Multi-technology card and PIN reader |